

BAYCO 5560-CHGR10

Cap Lamp 10 Bank Charging Station



Description

The 5560-CHGR10 Cap Lamp 10 Bank Charging Station has an aluminum housing with 10 glass-filled nylon chargers for use with the Nightstick XPR-5560 and XPR-5561 Cap Lamps. This charger can be mounted to a wall or to any solid surface outside of a hazardous environment. The Cap Lamps slide into place inside of the charger and lock securely in place. This bank charging station includes a 15 foot US Type B plug to AC power cord. Nightstick cap lamps sold separately.

Features and Benefits

- Fits Nightstick 5560 & 5561 Series Cap Lamps
- Aluminum housing with 10 glass-filled nylon chargers
- Stainless-steel charging pins
- Includes 15 foot US Type B plug to AC power cord
- Cap lamps sold separately
- Limited Lifetime Warranty

Tech Specs

UPC	17398805827
Length	13.5 in (343 mm)
Width	13.5 in (343 mm)
Depth	2.125 in (54 mm)
Weight	48 oz (1,361 g)
Case Material	Aluminum
Cord Length	15
Cord Color	Black
Power Source	AC Input: 100-240Vac 50/60 Hz, 3A
Package Contents	10 Bank Charging Station, 15 foot AC Power Cord (attached)
Warranty	Limited Lifetime
Certifications	CE, BC



Part No.	Description
5560-CHGR10	BAYCO Cap Lamp 10 Bank Charging Station



LISTED
E485423
ITE



Nightstick Model: 5560-CHGR10

Manufacturer: Bayco Products, Inc.
640 S. Sanden Blvd., Wylie, TX 75098

- For use only in non-hazardous locations
- For use with Nightstick Model: XPR-5560 & XPR-5561
- For use only with Fuse model 5SF 10-R (10A 250VAC)
- Class 1, 3-Pin (L, N FG)
- AC Input: 100-240V 50/60 Hz 3A
- DC Output: 5.5V D.C. Max. 500mA
- Operating Temperature -10°C to +40°C
- Storage Temperature -25°C to +85°C
- Relative Humidity 10 to +90%



WARNING: Cancer and Reproductive Harm
AVERTISSEMENT : Cancer et danger pour la reproduction
ADVERTENCIA: Cáncer y Daño Reproductivo
www.P65Warnings.ca.gov

Authorised Importer and Master Distributor

